

THREE PHASE RELAY TEST KIT / SECONDARY INJECTION TEST KIT Model - QRTK-3

Application:

- Protective Devices
- MCB
- Relays
- Overload coils
- Circuit breakers



Features

- Potential - free start and stop signal
- Continuously adjustable outputs
- Portable Models
- Digital Ammeter, Voltmeter and time interval meter (Unitimer)
- UniTimer automatically puts OFF the output, when timer reaches to its maximum value of the selected range to ensure safety of the instruments as well as the item under test. Wide range of measurement, i.e. From 0.001 second. To 9999 Seconds

Input	440V, 3 PHASE supply, 50Hz
Output	Three Phase Current O/p 1) 0 - 30 Amp each phase
Current Output is continuously variable & the Output is taken out through multi range CT. The secondary is connected to Ammeter scaled in 0 to 100%	
Double winding loading transformer of suitable burden to provided corresponding to the current output as specified	

AC Volt Output	Continuously variable 0 -230V Capacity -150 VA (Max) Single Phase
Time Measurement	0 - 0.001 to 9999 Sec in four ranges
Measuring CT	Multi ratio wound primary current transformer
Variable auto transformer	The Current output will be cutoff incase of any overload or even if the relay under test actuated
Current Metering	Digital Meter Basic Range : 0 - 1A AC Scaled in 0 to 100% for all selected range Accuracy : 1.5% of FSD
Voltage Metering	Digital Meter Basic Range : 0 - 230VAC Accuracy : 1.5% of FSD Fix Voltage : 63V, 110V and 230VAC

Technical Specification

- Input Supply: 440 V AC, ± 10% Three Phase
- Metering : a) 3 ½ Digit Ammeter / Voltmeter b) micro controlled based time interval meter
- Range : 0 - 0.001 to 9999 Sec in four ranges, selectable by a push button.
- Protection : Fuse / MCB, Over current protection

: We also manufacture

Primary Injection test kit
Circuit Breaker Timer / Time Interval test kit
Micro Ohm Meter
High Voltage Tester
Transformer Ratio Test kit
etc

Ordering Information

- Test Leads set- QRTK/5/LS
- Instruction Manual- QRTK/5/M

Simplified Measurements Solutions

Note: Size, shape, color and placement may be change for betterment of the product without any notice