

# Micro Ohm Meter

## Model : QRM-1S

### Application:

- Communication Cable
- Instrumentation Cable
- Transformer , Motors, Coil Manufacturer
- Transmission / Distribution
- Component Manufacturer
- Current Transformer Manufacturer
- Test Laboratories
- College Laboratories



### Features

- True Four Terminal Measurement
- Regulated and Highly stable 10 mA max Current Source
- 3 ½ Digital LCD Display
- 0.001 Ohm resolution on 200 Ohm range
- Protection against back EMF for high inductive loads
- Stable and fast measurement

Range	Max. Reading	Current	Resolution	Accuracy
2	1.999	0.01mA	0.001	±0.5% of rdg ±4 Digits
20	19.99	10mA	0.	±0.5% of rdg ±4 Digits

### Technical Specification

Range : 0.001 Ohm - 19.99 Ohm  
 Accuracy : ±0.5% of reading ± 4 Digit  
 Display : 3 ½ Digit LED Display

#### Standard Accessories

- One set of Test leads (1meters) with Crocodile clips
- Mains Cord
- User Manual
- Kelvin Clip test leads (optional)