



Lenovo™

# N 99

Start again, Chat with you all the way

**LENOVO TWO-WAY RADIO**

**16 Channel**

**Non Megnetic Speaker**

**Auto Battery save function**

**Louder Voice**



**Government Approved Licence Free Walkie FM Radio**

# N 99

## Product Parameters



### Basic Information

#### GENERAL INFORMATION

FREQUENCY	UHF: 446.000-446.2000Mhz
CHANNEL	16
PLL CHANNEL SPACING	12.5kHz/25KHz
BATTERY VOLTAGE	7.4V
BATTERY CAPACITY	3000mAh ( 11.1Wh)
DIMENSIONS	131x58x36mm (WITHOUT ANTENNA)
WEIGHT (WITH BATTERY AND ANTENNA)	450g

#### RECEIVER

RECEIVER SENSITIVITY	≤0.25uV
ADJACENT CHANNEL SELECTIVITY	≥60dB
BLOCKING	≥80dB
FM HARM AND NOISE	25k>45dB 125k>40dB
RECEIVE AUDIO POWER	>0.5W
AUDIO DISTORTION	≤5%
RF POWER OUTPUT	>0.5W

#### TRANSMITTER

MODULATION TYPE	16kΦF3E/8k F3E
MODULATION LIMIT	+5kHz/± 5kHz Φ
MODULATION DISTORTION	≤5%
RESIDUAL FM	-45dB
ADJACENT CHANNEL POWER	-67dB
RADIATED EMISSION	>0.5W

#### ENVIRONMENTAL INDICATORS

OPERATING TEMPERATURE	-20°C~+60°C
STORAGE TEMPERATURE	-20°C~+70°C
SHOCK AND VIBRATION	

ACCORDING GIB 150-2009 AND MIL-STD-810 C/D/E/F/G STANDARD.

THE ABOVE SPECIFICATIONS ARE TESTED IN ACCORDANCE WITH THE TIA/EIA-603 STANDARD.  
DUE TO THE CONTINUOUS UPDATING OF THE TECHNOLOGY, THE ABOVE INDICATOR DATA  
WILL BE CHANGED WITHOUT NOTICE.

Lenovo™